

DENON®

Product Information

AVR-X3200W



AVR-X3200W

7.2CH A/V SURROUND RECEIVER

POWERFUL 7.2CH A/V RECEIVER WITH WI-FI, BLUETOOTH®, 3D AUDIO, FULL 4K ULTRA HD SUPPORT AND MULTI-ZONE OPTIONS

Discover the thrilling world of immersive surround sound with the Denon AVR-X3200W A/V Receiver, which features Dolby Atmos® and DTS:X™ (via a future firmware update) surround decoding for the ultimate home theater experience. Full wireless connectivity is provided by both Wi-Fi and Bluetooth, with dual antennas that help ensure robust signal transmission and reception. Stream your favorite music from Internet radio stations, Spotify Connect® or local network stor-

age, and use AirPlay™ or Bluetooth to stream directly from a smart device. Control is made easy by the Denon AVR Remote app for iOS and Android™. Enjoy 4K Ultra HD video (including full HDCP 2.2 support) even from low resolution sources, thanks to the advanced video processor with upscaling power. And enjoy different video or audio content in a second zone through the multi-room/multi-source capabilities.



usa.denon.com

ca.denon.com

Built-in Bluetooth & Wi-Fi

Featuring Bluetooth & Wi-Fi wireless streaming connectivity, the AVR-X3200W is equipped with an advanced dual antenna RF transceiver system for robust and error-free streaming, even in congested urban environments. Connect to the internet through your home Wi-Fi network (or with a hard-wired connection via the RJ-45 Ethernet LAN port) and enjoy your favorite tracks from streaming music services such as Spotify Connect. You can also choose from thousands of internet radio stations around the world, and enjoy music from virtually every genre. With AirPlay, you can enjoy listening to your favorite tracks wirelessly from your iOS device, including the iPod touch®, iPhone® and iPad®, and the AVR-X3200W is also DLNA 1.5® certified for compatibility with your home PC or Mac. The Denon AVR Remote App lets you easily control the AVR-X3200W with your favorite portable device and it's available for both Apple and Android™ devices.

Latest HDMI 2.0a Connectivity; HDCP 2.2 Compatible; Video Scaling; ISF Certification

Equipped with 8 HDMI 2.0a inputs, including 1 conveniently located on the front panel, along with dual HDMI outputs, the AVR-X3200W incorporates an advanced video processor that features support for 4K Ultra HD 60 Hz full rate video, 4:4:4 Pure Color sub-sampling and 21:9 video pass-through, along with support for 3D content, HDR and BT.2020. The AVR-X3200W also features HDCP 2.2 compatibility on all HDMI inputs, a requirement for 4K Ultra HD copy-protected content. And, the video processor can also upscale analog and digital SD and HD video to 4K Ultra HD. Certified by the Imaging Science Foundation, the AVR-X3200W features a full suite of video calibration controls (for use by an ISF technician), along with ISF Day and ISF Night video modes.

KEY FEATURES [NEW]

- 7.2 channel A/V Receiver with 105W per channel
- Built-in Wi-Fi with dual antenna; built-in Bluetooth
- 4K/60 Hz full-rate pass-through and 4:4:4 color resolution, HDR, BT.2020
- Video Scaling of analog and digital video signal up to 4K 60/50Hz
- 8 HDMI 2.0a inputs (incl. 1 front) and 2 HDMI outputs with full HDCP 2.2 support
- Dolby Atmos (up to 5.1.2)
- DTS:X ready (via future firmware update)
- Audyssey MultEQ XT room equalization
- DSD, FLAC, ALAC and AIFF High Resolution audio streaming
- AirPlay, Spotify Connect, Pandora®, SiriusXM™ Internet Radio
- ECO mode with off/on/auto setting
- RS232 control, 7.2ch pre-outs
- Front panel USB input



Technical information

Number of Power Amps	7 (Front L/R, Center, Surround L/R, Surround Back L/R)	Preamplifier Section	
Power output	215 watts per channel Maximum Power Output Per Channel	Input sensitivity/impedance	200 mV / 47 kohms
	135 watts per channel (6 ohms, 1 kHz, THD 0.7%, 2ch driven)	Frequency response	10 Hz - 100 kHz — +1, -3 dB (DIRECT mode)
	105 watts per channel (8 ohms, 20 Hz - 20 kHz, THD 0.08%, 2ch driven)	S/N Ratio	100 dB (IHF-A weighted, DIRECT mode)
Speaker impedance	4 - 16 ohms	FM Section	
		Tuning frequency range	87.5 - 107.9 MHz
		AM Section	
		Tuning frequency range	520kHz - 1710kHz
		General	
		Power supply	AC 120 V, 60 Hz
		Power consumption	600 W (Standby 0.1 W, CEC standby 0.5 W)
		Power consumption No-Sound	45 W (ECO on), 80 W (ECO off)
		Dimensions (W x H x D)	17.1 x 6.6 x 15.3 in
		Weight	24.9 lbs.

[V01]

Easy To Setup, Easy To Use

With our exclusive Setup Assistant along with the Quick Start Guide, you can connect and configure your home theater system quickly and easily. The Setup Assistant features clear on-screen graphics and text that quickly and easily guide you through the setup process, optimizing critical system settings for the best possible sound quality. The Advanced Graphical User Interface and ergonomic remote control makes the daily operation a breeze.

Dolby Atmos Built In; DTS:X ready

For many years, movie surround soundtracks have been channel-based. Revolutionary Dolby Atmos surround sound technology dispenses with channel-based coding in favor of more advanced object-based coding, giving the sound designer the ability to precisely place sounds anywhere in the 3-dimensional space. Now, you can enjoy this same award-winning technology at home with the AVR-X3200W, which features the ability to connect a 5.1 surround sound speaker system and 2 additional overhead speakers or 2 additional Dolby Atmos-certified up-firing speakers for the ultimate home theater experience. Along with Dolby Atmos decoding and Dolby Surround Upmixing, the AVR-X3200W also features Dolby TrueHD lossless decoding and other Dolby Digital technologies.

The latest immersive surround sound system, DTS:X, features object-based audio coding that lets the sound designer place sonic elements anywhere in the 3D acoustic soundspace, and provides for overhead speakers to deliver a stunning surround sound experience. DTS:X and DTS Neural:X Upmixer will be enabled through a future online firmware update. For more info, please visit www.denon.com/dtsx.

STATE-OF-THE-ART DENON SOLUTIONS FOR MAXIMIZING CONTENT QUALITY

- Fully discrete, identical quality and power for all channels (7 channels, 105 watts per channel)
- Audyssey Dynamic Volume, for real-time volume adjustment
- Audyssey DynamicEQ, improves surround effects during low volume levels
- High-grade audio components
- High-performance 192kHz/24-bit D/A converters for all channels
- Multi-Source/Multi-Room (2nd zone via surround back speaker terminal or zone pre-out)
- Digitally transmitted Play function for iPod and iPhone (via USB) for best sound quality
- Optimized Bass redirection, for powerful bass performance in configurations without subwoofer

Powerful 7 Channel Discrete Amplifier with Eco Mode

Featuring high current discrete power output devices on all channels, the AVR-X3200W is rated at 105 watts per channel. For compatibility with the widest range of loudspeaker models, the AVR-X3200W is also equipped with low impedance drive capability, to provide operational stability with speakers rated at 4 ohms. The Eco mode adjusts the power amplifier's output according to the volume level to reduce power consumption and the on-screen Eco meter lets you see the power consumption reduction in real time.

Audyssey MultEQ XT

The AVR-X3200W features the Audyssey MultEQ XT suite of DSP functions, which includes includes room equalization, Dynamic EQ and Dynamic Volume. Audyssey MultEQ XT automatic room acoustic measurement and correction system matches your speakers to your room's acoustics, for the smoothest, most natural tonal balance. MultEQ XT provides greater filter precision for the main and satellite speakers, with 8 times the resolution compared to the base MultEQ system, at up to 8 measurement locations. Audyssey Dynamic EQ uses advanced psychoacoustic algorithms to continually adjust tonal balance so that the sound you hear is full range, even at lower volume levels, and Audyssey Dynamic Volume smoothes out annoying volume jumps, especially with loud commercials.

Multi-Source/Multi-Room

Enjoy 1 source in the main room, and listen to another source in another room. You have the option of connecting a pair of stereo speakers to 2 of the available amplifier channels for powered 2nd zone listening, or you can connect the 2nd zone via stereo pre-amp outputs. You can also connect the 2nd zone via HDMI, as the AVR-X3200W features dual HDMI outputs.

EASE-OF-USE AND OTHER FEATURES

- ECO mode
- Horizontal color-coded layout of speaker terminals for easy connection
- Label sheet for marking Speaker Wires & HDMI Cables
- Comes with simple, easy-to-use remote control handset
- Setup Assistant, providing easy-to-follow setup instructions, and Advanced Graphical User Interface with 3 languages
- Denon AVR Remote for iOS and Android
- 4 Quick Select buttons - can be used to store favorite sources, internet radio stations and preferred settings
- Standby HDMI Pass through
- Auto Standby and low power consumption at stand-by 0.1 W

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license.

Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories.

DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries.

The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses

Other trademarks and trade names are those of their respective owners.

Denon is a trademark or registered trademark of D&M Holdings, Inc.

* All specs can be subject to change

* Available only in Black

UPC	AVRX3200WBKE3	8-83795-00371-1	Black
-----	---------------	-----------------	-------

Ports

IN	HDMI (Front 1)	x 8
	Component	x 2
	Composite (video)	x 3
	Analog Audio	x 5
	Digital Optical	x 2
	Digital Coaxial	x 2
	USB (front)	x 1
OUT	HDMI Monitor	x 2
	Component	x1
	Zone2 Preout	2.0 ch
	Audio Preout (SW)	7.2 ch
	Phones	x 1
OTHER	Ethernet	x 1
	RS-232C	x 1
	Microphone Port	x 1
	FM Tuner Antenna	x 1
	AM Tuner Antenna	x 1

Denon Electronics (USA), LLC.

D&M Canada
100 Corporate Drive, Mahwah, New Jersey
07430 USA
TEL 201-762-6500

usa.denon.com ca.denon.com